PERFORMANCE MADE SMARTER



2-wire programmable transmitter

5333A


- RTD or Ohm input
- High measurement accuracy
- 3-wire connection
- Programmable sensor error value
- For DIN form B sensor head mounting

Application
- Linearized temperature measurement with Pt100...Pt1000 or Ni100...Ni1000 sensor.
- Conversion of linear resistance variation to a standard analog current signal, for instance from valves or Ohmic level sensors.

Technical characteristics
- Within a few seconds the user can program PR5333A to measure temperatures within all RTD ranges defined by the norms.
- The RTD and resistance inputs have cable compensation for 3-wire connection.

Mounting / installation
- For DIN form B sensor head or DIN rail mounting with the PR fitting type 8421.

Applications



This page is automatically generated on the basis of information provided on www.prelectronics.com and affiliated websites. It is provided to you as a service and for information purpose only. While we have attempted to maintain the information as accurately as possible, the page may contain errors or omissions for which we disclaim any and all liability

Order:

Type
5333A

Environmental Conditions

Operating temperature	-40°C to +85°C
Calibration temperature	20...28°C
Relative humidity	< 95% RH (non-cond.)
Protection degree (encl./terminal)	IP68 / IP00

Mechanical specifications

Dimensions	Ø 44 x 20.2 mm
Weight approx.	50 g
Wire size	1 x 1.5 mm^2 stranded wire
Screw terminal torque	0.4 Nm
Vibration	IEC 60068-2-6
2...25 Hz	±1.6 mm
25...100 Hz	±4 g

Common specifications

Supply

Supply voltage	8.0...35 VDC
Internal power dissipation	25 mW…0.8 W

Response time

Response time (programmable)	0.33...60 s
Voltage drop	8.0 VDC
Warm-up time	5 min.
Programming	Loop Link
Signal / noise ratio	Min. 60 dB
Accuracy	Better than 0.1% of sel. range
Signal dynamics, input	19 bit
Signal dynamics, output	16 bit
Effect of supply voltage change	< 0.005% of span / VDC
EMC immunity influence	< ±0.5% of span

Input specifications

Common input specifications

Max. offset	50% of selected max. value

RTD input

RTD type	Pt100, Ni100, lin. R
Cable resistance per wire	10 Ω (max.)
Sensor current	> 0.2 mA, < 0.4 mA
Effect of sensor cable resistance (3-wire)	< 0.002 Ω / Ω
Sensor error detection	Yes

Linear resistance input

Linear resistance min....max	0 Ω...10000 Ω

Output specifications

Current output

Signal range	4…20 mA
Min. signal range	16 mA
Load (@ current output)	≤ (Vsupply - 8) / 0.023 [Ω]
Load stability	≤ 0.01% of span / 100 Ω
Sensor error indication	Programmable 3.5…23 mA
NAMUR NE43 Upscale/Downscale	23 mA / 3.5 mA

Common output specifications

Updating time	135 ms
of span	= of the presently selected range

Observed authority requirements

EMC	2014/30/EU
EAC	TR-CU 020/2011

Approvals

ATEX 2014/34/EU	KEMA 10ATEX0003 X
IECEx	DEK 13.0036X
CSA	1125003
INMETRO	DEKRA 16.0014 X
DNV-GL Marine	Stand. f. Certific. No. 2.4