Specifications

Eaton 191111



Catalog Number: 191111

Eaton Moeller® series MSC-DM DOL starter, 380 V 400 V 415 V: 4 kW, Ir= 6.3 - 10 A, 24 V DC, DC voltage MSC-DM-10-M9(24VDC)/MSFA

General specifications

Product Name
Eaton Moeller® series MSC-DM DOL starter

Catalog Number
191111

EAN
4015081916092

Product Length/Depth
115 mm

Product Height
180 mm

Product Width
45 mm

Product Weight
0.767 kg

Certifications
CSA-C22.2 No. 14 (on request)
UL 508 (on request)

Powering Business Worldwide

Features & Functions

Fitted with:

Short-circuit release

Functions

Temperature compensated overload protection

General

Class

CLASS 10 A

Connection

Screw terminals

Connection to SmartWire-DT

No

Coordination type

1

Degree of protection

IP20

NEMA Other

Model

IEC starter

Mounting method

Motor starter Feeder System

Number of auxiliary contacts (normally closed contacts)

0

Number of auxiliary contacts (normally open contacts)

1

Overload release current setting - min

6.3 A

Overload release current setting - max

10 A

Overvoltage category

III

Pollution degree

3

Rated impulse withstand voltage (Uimp)

6000 V AC

Suitable for

Also motors with efficiency class IE3

Type

Starter with Bi-Metal release

Voltage type

DC

Climatic environmental conditions

Altitude

Max. 2000 m

Ambient operating temperature - min

-25 °C

Ambient operating temperature - max

55 °C

Electrical rating

Rated operational current (Ie)

8.5 A

Rated operational current (Ie) at AC-3, 380 V, 400 V, 415 V

9 A

Rated operational power at AC-3, 220/230 V, 50 Hz

2.2 kW

Rated operational power at AC-3, 380/400 V, 50 Hz

4 kW

Rated operational voltage

230 - 415 V AC

Short-circuit rating

Rated conditional short-circuit current (Iq), type 2, 380 V, 400 V, 415 V

100 A

Short-circuit release (Irm) - max

155 A

Magnet system

Power consumption (sealing) at DC

2.6 W

Rated control supply voltage (Us) at AC, 50 Hz - min

0 V

Rated control supply voltage (Us) at AC, 50 Hz - max

0 V

Rated control supply voltage (Us) at AC, 60 Hz - min

0 V

Rated control supply voltage (Us) at AC, 60 Hz - max

0 V

Rated control supply voltage (Us) at DC - min

24 V

Rated control supply voltage (Us) at DC - max

24 V

Design verification

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Resources

Brochures

eaton-motor-starters-system-xstart-brochure-br03407001en-en-us.pdf

eaton-msfs-motor-starter-feeder-system-brochure-br034005en-en-us.pdf

Catalogs

eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 Inscriptions

Meets the product standard's requirements.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

10.8 Connections for external conductors

Is the panel builder's responsibility.

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

Product Range Catalog Switching and protecting motors

Drawings

eaton-manual-motor-starters-msc-d-dol-starter-dimensions-005.eps

eaton-manual-motor-starters-msc-d-dol-starter-3d-drawing-003.eps

eaton-general-ie-ready-dilm-contactor-standards.eps

eCAD model

ETN.191111.edz

Installation instructions

IL034030ZU

IL015082ZU.pdf

Installation videos

WIN-WIN with push-in technology

mCAD model

DA-CD-msc_dm_mfsa

DA-CS-msc_dm_mfsa

Sales notes

eaton-link-module-for-motor-starters-pkz-flyer-fl034003en-en-us.pdf

Wiring diagrams

eaton-manual-motor-starters-device-msc-d-dol-starter-wiring-diagram.eps

10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Eaton.com/socialmedia