Specifications

# Eaton 035261

## Catalog Number: 035261

Eaton Moeller® series STI Control transformer, 4 kVA, Rated input voltage 400± 5 % V, Rated output voltage 230 V



### General specifications

**Product Name**
Eaton Moeller® series STI Control transformer

**Catalog Number**
035261

**EAN**
4015080352617

**Product Length/Depth**
200 mm

**Product Height**
255 mm

**Product Width**
230 mm

**Product Weight**
32.9 kg

**Certifications**
IEC/EN 61558-2-2
UL 506
UL report applies to both US and Canada
UL5085-1
CE
Certified by UL for use in Canada
CSA-C22.2 No. 66
UL File No.: E167225
IEC/EN 60204-1, ÖVE-EN 13
VDE 0570 Part 2 -6 (safety transformers)
UL 5085-2
CSA-C22.2 No. 66.1-06
IEC/EN 61558-2-2/2-4/2-6
UL Category Control No.: XPTQ2, XPTQ8
VDE 0113, VDE 0100 Part 410
VDE 0570 Part 2-2

**Catalog Notes**
Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature of 20 °C

Powering Business Worldwide

## Features & Functions

### Features

Fully Vacuum-impregnated

Reinforced insulation

Separate windings

## General

### Ambient operating temperature - min

-25 °C

### Ambient operating temperature - max

40 °C

### Connection lug

Yes for > 115 A

### Connection type

Terminations, < 115 A

### Duty factor

100 %

### Insulation class

B

### Primary tapping

± 5 %

### Product category

Single-phase control transformers ST

### Suitable for

Branch circuits, (UL/CSA)

### Type

Single-phase control, isolating and safety transformer

## Electrical rating

### Efficiency

97 %

### No-load losses

38 W

### Rated frequency - min

50 Hz

### Rated frequency - max

60 Hz

### Rated power

4 VA

### Relative short-circuit voltage

2.2 %

## Design verification

### Equipment heat dissipation, current-dependent Pvid

0 W

### Heat dissipation capacity Pdiss

0 W

### Heat dissipation per pole, current-dependent Pvid

0 W

### Rated operational current for specified heat dissipation (In)

0 A

### Static heat dissipation, non-current-dependent Pvs

126 W

### 10.2.2 Corrosion resistance

Meets the product standard's requirements.

Short-circuit losses

88 W

Short-time rating

15 kVA

Voltage rating - max

600 V

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 Inscriptions

Meets the product standard's requirements.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

10.8 Connections for external conductors

Is the panel builder's responsibility.

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

### 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

### 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## Resources

### Application notes

eaton-transformer-stz-sti-stn-dtz-uti-ap009002-en-us.pdf

### Brochures

eaton-transformers-brochure-br009002en-en-us.pdf

### Catalogs

eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf

### Declarations of conformity

DA-DC-00004421.pdf

DA-DC-00004447.pdf

### Drawings

eaton-general-transformer-sti-control-transformer-dimensions-024.eps

### eCAD model

DA-CE-ETN.STI4,0(400_230)

### mCAD model

DA-CS-sti4_0_230

DA-CD-sti4_0_230

### System overview

eaton-general-diagram-sti-control-transformer-explosion-drawing-002.eps



© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.