Specifications

Eaton 198524



Catalog Number: 198524

Eaton Moeller® series Rapid Link - DOL starter, 6.6 A, Sensor input 2, 400/480 V AC, AS-Interface®, S-7.4 for 31 modules, HAN Q5, with manual override switch

General specifications

Product Name
Eaton Moeller® series Rapid Link DOL starter

Catalog Number
198524

EAN
4015081963997

Product Length/Depth
120 mm

Product Height
270 mm

Product Width
220 mm

Product Weight
1.8 kg

Certifications
IEC/EN 60947-4-2
RoHS
UL 60947-4-2
CCC
UL approval
CE

Catalog Notes
Assigned motor rating: for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm at 50 Hz or 1800 min at 60 Hz

Powering Business Worldwide

Product specifications

Type

DOL starter

Features

Parameterization: drivesConnect mobile (App)
Parameterization: Fieldbus
Parameterization: Keypad
Diagnostics and reset on device and via AS-Interface
Parameterization: drivesConnect

10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

Resources

Application notes

Generation Change RASP4 to RASP5

Configuration to Rockwell PLC for Rapid Link

Connecting drives to generator supplies

Generation Change RA-SP to RASP5

Generation change from RA-SP to RASP 4.0

Generation change from RA-MO to RAMO 4.0

Generation change RAMO4 to RAMO5

Electromagnetic compatibility (EMC)

Brochures

eaton-rapid-link-5-brochure-br040014en-en-us.pdf

eaton-powerxl-variable-frequency-drives-material-handling-brochure-br040017en-en-us.pdf

DA-SW-drivesConnect

Catalogs

eaton-rapid-link-5-drive-system-catalog-ca040002en-en-us

Product Range Catalog Drives Engineering

Declarations of conformity

DA-DC-00003964.pdf

DA-DC-00004523.pdf

DA-DC-00004525.pdf

DA-DC-00004184.pdf

Drawings

eaton-bus-adapter-rapidlink-reversing-starter-dimensions-003.eps

eaton-bus-adapter-rapidlink-reversing-starter-dimensions-002.eps

eaton-bus-adapter-rapidlink-speed-controller-dimensions-003.eps

eaton-bus-adapter-rapidlink-speed-controller-dimensions-002.eps

eCAD model

ETN.RAMO5-D204A31-512RS1.edz

Installation instructions

IL034084ZU

Installation videos

Rapid Link 5

Manuals and user guides

MN034004EN

MN040003_EN

10.2.7 Inscriptions

Meets the product standard's requirements.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

10.8 Connections for external conductors

Is the panel builder's responsibility.

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

Fitted with:

Thermo-click
Electronic motor protection
Thermistor monitoring PTC
Key switch position AUTO
Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation
Manual override switch
Short-circuit release
Key switch position OFF/RESET
Key switch position HAND

Class

CLASS 10 A

Lifespan, electrical

10,000,000 Operations (at AC-3)

Climatic proofing

In accordance with IEC/EN 50178

mCAD model

ramo5_v4.dwg

ramo5_v4.stp

< 95 %, no condensation

Rated impulse withstand voltage (Uimp)

4000 V

Model

Direct starter

Altitude

Max. 1000 m

Max. 2000 m

Above 1000 m with 1 % performance reduction per 100 m

Lifespan, mechanical

10,000,000 Operations (at AC-3)

Mains switch-on frequency

Maximum of one time every 60 seconds

Electrical connection type of main circuit

Plug-in connection

Mains voltage tolerance

380 - 480 V (-15 %/+10 %, at 50/60 Hz)

Voltage type

DC

Mounting position

Vertical

Rated conditional short-circuit current (Iq)

10 kA

Overvoltage category

III

Connection

Connections pluggable in power section

Off-delay

20 - 35 ms

Functions

External reset possible

For actuation of motors with mechanical brake

Temperature compensated overload protection

On-delay

20 - 35 ms

System configuration type

Center-point earthed star network (TN-S network)

AC voltage

Phase-earthed AC supply systems are not permitted.

Braking current

≤ 0.6 A (max. 6 A for 120 ms), Actuator for external motor brake

Electromagnetic compatibility

Class A

Current limitation

Adjustable, motor, main circuit

0.3 - 6.6 A, motor, main circuit

Output frequency

50/60 Hz

Braking voltage

400/480 V AC -15 % / +10 %, Actuator for external motor brake

Overload cycle

AC-53a

Overload release current setting - min

0.3 A

Rated conditional short-circuit current (Iq), type 2, 230 V

0 A

Rated conditional short-circuit current (Iq), type 2, 380 V, 400 V, 415 V

0 A

Rated conditional short-circuit current, type 1, 480 Y/277 V

10000 A

Rated conditional short-circuit current, type 1, 600 Y/347 V

0 A

Rated control supply voltage (Us) at AC, 50 Hz - max

0 V

Rated control supply voltage (Us) at AC, 50 Hz - min

0 V

Rated control supply voltage (Us) at AC, 60 Hz - max

0 V

Rated control supply voltage (Us) at AC, 60 Hz - min

0 V

Rated control supply voltage (Us) at DC - max

0 V

Rated control supply voltage (Us) at DC - min

0 V

Rated frequency - max

63 Hz

Rated frequency - min

47 Hz

Rated operational current (Ie) at 150% overload

6.6 A

Rated operational current (Ie) at AC-3, 380 V, 400 V, 415 V

6.6 A

Shock resistance

15 g, Mechanical, According to IEC/EN 60068-2-27, 11 ms, Half-sinusoidal shock 11 ms, 1000 shocks per shaft

Interfaces

Specification: S-7.4 (AS-Interface®)
Max. total power consumption from AS-Interface® power supply unit (30 V): 190 mA
Number of slave addresses: 31 (AS-Interface®)

Protocol

AS-Interface profile cable: S-7.4 for 31 modules
ASI

Rated control voltage (Uc)

400/480 V AC (external brake 50/60 Hz)
24 V DC (-15 %/+20 %, external via AS-Interface® plug)

Supply frequency

50/60 Hz, fLN, Main circuit

Rated operational current (Ie)

6.6 A

Rated operational power at 380/400 V, 50 Hz - max

3 kW

Rated operational power at 380/400 V, 50 Hz - min

0.09 kW

Rated operational voltage

480 V AC, 3-phase
400 V AC, 3-phase

Short-circuit protection (external output circuits)

Type 1 coordination via the power bus' feeder unit, Main circuit

Vibration

Resistance: 57 Hz, Amplitude transition frequency on acceleration
Resistance: 6 Hz, Amplitude 0.15 mm
Resistance: 10 - 150 Hz, Oscillation frequency
Resistance: According to IEC/EN 60068-2-6

Ambient operating temperature - max

55 °C

Ambient operating temperature - min

-10 °C

Ambient storage temperature - max

70 °C

Ambient storage temperature - min

-40 °C

Assigned motor power at 460/480 V, 60 Hz, 3-phase

3 HP

Number of auxiliary contacts (normally closed contacts)

0

Number of auxiliary contacts (normally open contacts)

0

Number of command positions

1

Number of pilot lights

0

Overload release current setting - max

6.6 A

Rated operational power at AC-3, 220/230 V, 50 Hz

0 kW

Rated operational power at AC-3, 380/400 V, 50 Hz

3 kW

Rated power at 460 V, 60 Hz, 3-phase

2.238 kW

Rated power at 575 V, 60 Hz, 3-phase

0 kW

Product category

Motor starter

Cable length

10 m, Radio interference level, maximum motor cable length

Coordination class (IEC 60947-4-3)

Class 1

Degree of protection

IP65

NEMA 12

Electrical connection type for auxiliary- and control-current circuit

Plug-in connection

Input current

6.6 A (at 150 % Overload)

Power consumption

8 W

Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Eaton.com/socialmedia