Specifications

Eaton 197501



Catalog Number: 197501

Eaton DA1 Frequency inverter, 500 V AC, 3-phase, 43 A, 30 kW, IP20/NEMA 0, Additional PCB protection, FS5

General specifications

Product Name
Eaton DA1 Variable frequency drive

Catalog Number
197501

EAN
4015081940769

Product Length/Depth
261 mm

Product Height
485 mm

Product Width
234 mm

Product Weight
18.2 kg

Certifications
IEC/EN 61800-3
UL Category Control No.: NMMS, NMMS7
UL File No.: E172143
IEC/EN 61800-2
Safety: EN 61800-5-1: 2003
Certified by UL for use in Canada
CUL
CE
IEC/EN61800-3
UkrSEPRO
UL 508C
EAC
UL
UL report applies to both US and Canada
IEC/EN61800-5
RCM
RoHS, ISO 9001

Catalog Notes
The brake resistors are assigned based on the maximum rated power of the

General

Cable length

200 m, screened, with motor choke, maximum permissible cable length

100 m, screened, maximum permissible cable length

150 m, unscreened, maximum permissible cable length

200 m, unscreened, with motor choke, maximum permissible cable length

Communication interface

EtherCAT, optional

OP-Bus (RS485)

Modbus-TCP, optional

PROFINET, optional

Modbus RTU

Ethernet IP, optional

DeviceNet, optional

PROFIBUS, optional

CANopen®

SmartWire-DT, optional

Connection to SmartWire-DT

In conjunction with DX-NET-SWD1 SmartWire DT module

Yes

Degree of protection

IP20

NEMA Other

Fitted with:

Brake chopper

Internal DC link

IGBT inverter

Additional PCB protection

PC connection

Control unit

OLED display

Breaking resistance

Frame size

FS5

Functions

4-quadrant operation possible

Mounting position

Vertical

Product Category

Variable frequency drives

Climatic environmental conditions

Ambient operating temperature - min

-10 °C

Altitude

Above 1000 m with 1 % derating per 100 m

Max. 1000 m

Max. 4000 m

Ambient operating temperature - max

50 °C

Ambient operating temperature at 150% overload - min

-10 °C

Ambient operating temperature at 150% overload - max

50 °C

Ambient storage temperature - min

-40 °C

Ambient storage temperature - max

60 °C

Climatic proofing

< 95 average relative humidity (RH), no condensation, no corrosion

Main circuit

Efficiency

97.9 % (η)

Heat dissipation at current/speed

202 W at 25% current and 0% speed

243 W at 25% current and 50% speed

268 W at 50% current and 0% speed

338 W at 50% current and 50% speed

383 W at 50% current and 90% speed

480 W at 100% current and 0% speed

591 W at 100% current and 50% speed

707 W at 100% current and 90% speed

Input current ILN at 150% overload

49.5 A

Leakage current at ground IPE - max

43 mA

Mains switch-on frequency

Protection

Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)

Protocol

PROFIBUS
PROFINET IO
Other bus systems
CAN
MODBUS
EtherNet/IP
TCP/IP
DeviceNet

Safety function/level

STO (Safe Torque Off, SIL2, PLc Cat 2)

Suitable for

Branch circuits, (UL/CSA)

Maximum of one time every 30 seconds

Mains voltage - min

500 V

Mains voltage - max

600 V

Operating mode

Sensorless vector control (SLV)
Optional: Vector control with feedback (CLV)
Speed control with slip compensation
U/f control

Output frequency - min

0 Hz

Output frequency - max

500 Hz

Output voltage (U2)

600 V AC, 3-phase
500 V AC, 3-phase

Overload current IL at 150% overload

64.5 A

Rated control supply voltage

10 V DC (Us, max. 10 mA)

Rated frequency - min

48 Hz

Rated frequency - max

62 Hz

Rated operational current (Ie) at 150% overload

43 A

Rated operational power at 500 V, 50 Hz, 3-phase

30 kW

Rated operational power at 525 V, 50 Hz, 3-phase

30 kW

Rated operational voltage

500 V AC, 3-phase
600 V AC, 3-phase

Resolution

0.1 Hz (Frequency resolution, setpoint value)

Short-circuit protection

NH fuse used together with TB00-D fuse base, Power wiring, Assigned switching and protective elements

LPJ fuse used together with JM60100-3 fuse base, Power wiring, Assigned switching and protective elements

Short-circuit protection rating

63 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring

Starting current - max

200 %, IH, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section

Supply frequency

50/60 Hz

Switching frequency

8 kHz, 4 - 24 kHz adjustable (audible), fPWM, Power section, Main circuit

System configuration type

AC supply systems with earthed center point

Voltage rating - max

600 VAC

Motor rating

Assigned motor current IM at 500 V, 50 Hz, 150% overload

43 A

Assigned motor current IM at 525 V, 50 Hz, 150% overload

42 A

Assigned motor current IM at 550 - 600 V, 60 Hz, 150% overload

41 A

Assigned motor power at 575/600 V, 60 Hz, 3-phase

40 HP

Apparent power

Apparent power at 600 V

44.69 kVA

Braking function

Braking resistance

16 Ω

Braking torque

Max. 30 % MN, Standard - Main circuit

Adjustable to 100 % (DC)

Max. 100 % of rated operational current Ie with external braking resistor - Main circuit

Switch-on threshold for the braking transistor

975 VDC

Control circuit

Number of inputs (analog)

2

Number of inputs (digital)

5

Number of outputs (analog)

2

Number of outputs (digital)

2

Number of relay outputs

Design verification

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

2 (parameterizable, 1 N/O and 1 changeover contact, 6 A (250 V, AC-1) / 5 A (30 V, DC-1))

Rated control voltage (Uc)

24 V DC (external, max. 100 mA)

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 Inscriptions

Meets the product standard's requirements.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

10.8 Connections for external conductors

Is the panel builder's responsibility.

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Resources

Application notes

Master slave operation

Connecting drives to generator supplies

Update DX-COM-STICK3

Electromagnetic compatibility (EMC)

How does the internal motor protection work?

Operating Permanent Magnet and Brushless DC Motors

Hoist applications

Motor data Motor Protection V/f curves for induction motors

Dependency of the output current on switching frequency and ambient temperature

Conformal Coating

The OP System Bus - Parameterizing - Control

I/O Configuration

Vector Control of Induction Motors

Closed Loop Vector Control

Equal load sharing with the droop function

Setpoint Setting

DX-COM-STICK3_Connection

Starting, Stopping and Operation

Dual Rating What exactly does that mean?

Use of multiple ramps

Access to Parameter Level 2 and 3 Parameter Lock RESET

PID controller

Brochures

eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf

DA-SW-DA1 Profinet ConfigFile

DA-SW-DA1 Profinet Library

DA-SW-drivesConnect

DA-SW-DA1 Profinet GSDML V2.25 Config File

Catalogs

Product Range Catalog Drives Engineering

Declarations of conformity

DA-DC-00004672.pdf

DA-DC-00003964.pdf

DA-DC-00004184.pdf

Drawings

eaton-frequency-inverter-dimensions-013.eps

eCAD model

DA-CE-ETN.DA1-35041NB-B20C

Installation instructions

eaton-da1-variable-frequency-drive-il040049zu.pdf

Installation videos

Video PowerXL DA1

PowerXL Variable Frequency Drives DC1 and DA1 - EN

Manuals and user guides

MN040003_EN

MN040018_EN

eaton-canopen-communication-manual-for-variable-frequency-drives-variable-speed-starters-da1-db1-dc1-de11-mn040019-en-us.pdf

MN04020006Z_EN

MN04020005Z_EN

eaton-da1-variable-frequency-drive-mn040063-en-us.pdf

mCAD model

DA-CD-da1_fs4_ip20

DA-CS-da1_fs4_ip20

Multimedia

System solutions based on EtherCAT

Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments?

Product notifications

eaton-drives-ecodesign-directive-mz040046en-en.pdf

Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Eaton.com/socialmedia