Specifications

# Eaton 199582



## Catalog Number: 199582

Eaton Moeller® series MSC-D DOL starter, 380 V 400 V 415 V: 7.5 kW, Ir= 10 - 16 A, 24 V DC, DC, Push in terminals MSC-D-16-M15(24VDC)-PI

### General specifications

**Product Name**
Eaton Moeller® series MSC-D DOL starter

**Catalog Number**
199582

**EAN**
4015081982837

**Product Length/Depth**
95 mm

**Product Height**
197 mm

**Product Width**
45 mm

**Product Weight**
0.673 kg

**Certifications**
IEC/EN 60947-4-1
VDE 0660

**Catalog Notes**
Not suitable for motors with efficiency class IE3.

Powering Business Worldwide

## Features & Functions

Fitted with:

Short-circuit release

Functions

Temperature compensated overload protection

## General

Class

CLASS 10 A

Connection

Push in terminals

Connection to SmartWire-DT

No

Coordination type

1

Degree of protection

IP20

NEMA Other

Model

IEC/UL starter

Mounting method

DIN rail

Number of auxiliary contacts (normally closed contacts)

0

Number of auxiliary contacts (normally open contacts)

1

Overload release current setting - min

10 A

Overload release current setting - max

16 A

Overvoltage category

III

Pollution degree

3

Rated impulse withstand voltage (Uimp)

6000 V AC

Type

Starter with Bi-Metal release

Voltage type

DC

## Climatic environmental conditions

## Electrical rating

Altitude

Max. 2000 m

Ambient operating temperature - min

-25 °C

Ambient operating temperature - max

55 °C

Rated operational current (Ie)

15.2 A

Rated operational current (Ie) at AC-3, 380 V, 400 V, 415 V

15 A

Rated operational power at AC-3, 220/230 V, 50 Hz

4 kW

Rated operational power at AC-3, 380/400 V, 50 Hz

7.5 kW

Rated operational voltage

230 - 415 V AC

## Short-circuit rating

Rated conditional short-circuit current (Iq), type 2, 380 V, 400 V, 415 V

50000 A

Short-circuit release (Irm) - max

248 A

## Magnet system

Power consumption (sealing) at DC

2.6 W

Rated control supply voltage (Us) at AC, 50 Hz - min

0 V

Rated control supply voltage (Us) at AC, 50 Hz - max

0 V

Rated control supply voltage (Us) at AC, 60 Hz - min

0 V

Rated control supply voltage (Us) at AC, 60 Hz - max

0 V

Rated control supply voltage (Us) at DC - min

24 V

Rated control supply voltage (Us) at DC - max

24 V

## Design verification

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

## Resources

Brochures

eaton-motor-starters-system-xstart-brochure-br03407001en-en-us.pdf

eaton-msfs-motor-starter-feeder-system-brochure-br034005en-en-us.pdf

Catalogs

Product Range Catalog Switching and protecting motors

eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf

Declarations of conformity

Meets the product standard's requirements.

### 10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

### 10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

### 10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

### 10.2.7 Inscriptions

Meets the product standard's requirements.

### 10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

### 10.4 Clearances and creepage distances

Meets the product standard's requirements.

### 10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

### 10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

### 10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

### 10.8 Connections for external conductors

Is the panel builder's responsibility.

### 10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

### 10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

### 10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

### 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

### 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

DA-DC-00004913.pdf

DA-DC-00004881.pdf

## Drawings

eaton-manual-motor-starters-motortsarter-msc-d-dol-starter-dimensions.eps

## eCAD model

ETN.199582.edz

## Installation instructions

eaton-push-in-dol-msc-d-up-to-15a-il034096zu.pdf

## Installation videos

WIN-WIN with push-in technology

## mCAD model

msc_d_bg1_pi.dwg

msc_d_bg1_pi.stp

## Sales notes

eaton-link-module-for-motor-starters-pkz-flyer-fl034003en-en-us.pdf

### 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

### 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

---

Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Eaton.com/socialmedia