Specifications

Eaton 121760

Catalog Number: 121760

Eaton Moeller® series MSC-DEA DOL starter, 380 V 400 V 415 V: 11 kW, 100 kA, Ir: 8 - 32 A, Connection to SmartWire-DT: yes, 24 V DC, DC Voltage



General specifications

Product Name
Eaton Moeller® series MSC-DEA DOL starter

Catalog Number
121760

EAN
4015081195701

Product Length/Depth
128 mm

Product Height
242 mm

Product Width
45 mm

Product Weight
1.125 kg

Certifications
VDE 0660
IEC/EN 60947-4-1

Powering Business Worldwide

Features & Functions

Fitted with:

Short-circuit release

Functions

Temperature compensated overload protection

General

Class

Adjustable

Connection

Screw terminals

Connection to SmartWire-DT

Yes

In conjunction with PKE-SWD-32 SmartWire DT PKE module

Coordination type

2

Current flow times - min

1000 (Class 20) AC-4 cycle operation, Main conducting paths
700 (Class 10) AC-4 cycle operation, Main conducting paths
500 (Class 5) AC-4 cycle operation, Main conducting paths
For all combinations with an SWD activation, you need not adhere to the minimum current flow times and minimum cut-out periods.
900 (Class 15) AC-4 cycle operation, Main conducting paths
Note: Going below the minimum current flow time can cause overheating of the load (motor).

Cut-out periods - min

≤ 500 ms, main conducting paths, AC-4 cycle operation

Degree of protection

IP20

NEMA Other

Model

IEC starter

Mounting method

DIN rail

Number of auxiliary contacts (normally closed contacts)

1

Number of auxiliary contacts (normally open contacts)

0

Overload release current setting - min

8 A

Overload release current setting - max

32 A

Overvoltage category

III

Pollution degree

3

Protocol

Other bus systems

Rated impulse withstand voltage (Uimp)

6000 V AC

Suitable for

Also motors with efficiency class IE3

Type

Starter with electronic trip unit

Voltage type

DC

Climatic environmental conditions

Ambient operating temperature - min

-25 °C

Ambient operating temperature - max

55 °C

Electrical rating

Rated operational current (Ie)

21.7 A

Rated operational current (Ie) at AC-3, 380 V, 400 V, 415 V

25 A

Rated operational current (Ie) at AC-3, 500 V

23.4 A

Rated operational power at AC-3, 220/230 V, 50 Hz

5.5 kW

Rated operational power at AC-3, 380/400 V, 50 Hz

12.5 kW

Rated operational power at AC-3, 500 V, 50 Hz

15 kW

Rated operational voltage

230 - 415 V AC

Short-circuit rating

Rated conditional short-circuit current (Iq), 500 V

50 A

Rated conditional short-circuit current (Iq), type 2, 380 V, 400 V, 415 V

100000 A

Short-circuit release (Irm) - max

496 A

Magnet system

Power consumption (sealing) at DC

0.86 W

Rated control supply voltage (Us) at AC, 50 Hz - min

0 V

Rated control supply voltage (Us) at AC, 50 Hz - max

0 V

Rated control supply voltage (Us) at AC, 60 Hz - min

0 V

Rated control supply voltage (Us) at AC, 60 Hz - max

0 V

Rated control supply voltage (Us) at DC - min

24 V

Rated control supply voltage (Us) at DC - max

24 V

Design verification

Equipment heat dissipation, current-dependent Pvid

17.8 W

Heat dissipation capacity Pdiss

0 W

Heat dissipation per pole, current-dependent Pvid

5.9 W

Rated operational current for specified heat dissipation (In)

25 A

Static heat dissipation, non-current-dependent Pvs

0.86 W

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 Inscriptions

Meets the product standard's requirements.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be

evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

10.8 Connections for external conductors

Is the panel builder's responsibility.

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Resources

Brochures

eaton-msfs-motor-starter-feeder-system-brochure-br034005en-en-us.pdf

eaton-motor-starters-system-xstart-brochure-br03407001en-en-us.pdf

Catalogs

Product Range Catalog Switching and protecting motors

eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf

Declarations of conformity

DA-DC-00004996.pdf

DA-DC-00004992.pdf

Drawings

eaton-manual-motor-starters-dol-starter-msc-d-dimensions.eps

eaton-manual-motor-starters-mounting-msc-d-dol-starter-3d-drawing.eps

eaton-manual-motor-starters-dol-starter-msc-d-3d-drawing-002.eps

eaton-general-ie-ready-dilm-contactor-standards.eps

eCAD model

ETN.121760.edz

Installation instructions

IL03402010Z

Installation videos

WIN-WIN with push-in technology

mCAD model

DA-CD-msc_de_bg2

DA-CS-msc_de_bg2

Sales notes

eaton-link-module-for-motor-starters-pkz-flyer-fl034003en-en-us.pdf

Wiring diagrams

eaton-manual-motor-starters-msc-d-dol-starter-wiring-diagram.eps



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



Eaton.com/socialmedia