Especificaciones

# Eaton FNQ-14

## Catalog Number: FNQ-14

Eaton Bussmann series FNQ fuse, Time-delay, Motor control transformers, Circuits with in-rush currents, 14 A, Non-indicating, Ferrule end x ferrule end, 10 kAIC at 500 Vac, Nickel-plated bronze endcap, Standard, 500 V




### General specifications

| | |
|---|---|
| **Product Name** | **Catalog Number** |
| Eaton Bussmann series FNQ fuse | FNQ-14 |
| **UPC** | **EAN** |
| 051712786348 | 5027590407588 |
| **Product Length/Depth** | **Product Height** |
| 0.39 in | 1.44 in |
| **Product Width** | **Product Weight** |
| 0.39 in | 0.2 lb |
| **Compliances** | **Certifications** |
| CE Marked<br>RoHS Compliant | Contact factory |

Powering Business Worldwide

## Especificaciones del producto

### Type

Time-delay Midget fuse

### Application

Motor control transformers, circuits with in-rush currents

### Amperage Rating

14 A

### Class

Supplemental

### Interrupt rating

10 kAIC at 500 Vac

### Fuse indicator

Non-indicating

### Connection

Ferrule end x ferrule end

### Material

Nickel-plated bronze endcap

### Packaging type

Standard

### Quantity

10

### Voltage rating

500 V

## Recursos

Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

© 2024 Eaton. Todos los derechos reservados.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Eaton.com/socialmedia