

# AC Compact Fan Kits

Kits incorporating a range of AC fans, a power lead and either a metal guard or an air filter option.

- 230V fans
- Can be operated at 50 or 60Hz
- Metal fan housings
- IP20 Protection
- Lead 610mm
- Filter pads that can be changed without switching off the fan

| Part Number | Airflow M3/h | Airflow CFM | Voltage V | Noise dB(A) | Bearings | Power W | Speed RPM | Temperature Range °C | Length mm | Width mm | Depth mm | Fan Type | Lead | Guard | Filter |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| 9956L-KR0 | 84 | 49.4 | 230 | 29 | BB | 9.5 | 1850 | -40...+80 | 119 | 119 | 25 | 9956L | LZ120/1.5 | LZ30K | - |
| 9956L-KR1 | 84 | 49.4 | 230 | 29 | BB | 9.5 | 1850 | -40...+80 | 119 | 119 | 25 | 9956L | LZ120/1.5 | - | PMFA120T |
| 9956-KR0 | 117 | 68.9 | 230 | 37 | BB | 14.0 | 2450 | -40...+70 | 119 | 119 | 25 | 9956 | LZ120/1.5 | LZ30K | - |
| 9956-KR1 | 117 | 68.9 | 230 | 37 | BB | 14.0 | 2450 | -40...+70 | 119 | 119 | 25 | 9956 | LZ120/1.5 | - | PMFA120T |
| 4890N-KR0 | 80 | 47.1 | 230 | 25 | SB | 11.0 | 1550 | -10...+70 | 119 | 119 | 38 | 4890N | LZ120/1.5 | LZ30K | - |
| 4890N-KR1 | 80 | 47.1 | 230 | 25 | SB | 11.0 | 1550 | -10...+70 | 119 | 119 | 38 | 4890N | LZ120/1.5 | - | PMFA120T |
| 4850N-KR0 | 100 | 58.9 | 230 | 32 | SB | 10.0 | 1800 | -10...+70 | 119 | 119 | 38 | 4850N | LZ120/1.5 | LZ30K | - |
| 4850N-KR1 | 100 | 58.9 | 230 | 32 | SB | 10.0 | 1800 | -10...+70 | 119 | 119 | 38 | 4850N | LZ120/1.5 | - | PMFA120T |
| 4650N-KR0 | 160 | 94.2 | 230 | 46 | SB | 19.0 | 2650 | -10...+55 | 119 | 119 | 38 | 4650N | LZ120/1.5 | LZ30K | - |
| 4650N-KR1 | 160 | 94.2 | 230 | 46 | SB | 19.0 | 2650 | -10...+55 | 119 | 119 | 38 | 4650N | LZ120/1.5 | - | PMFA120T |
| 4656N-KR0 | 160 | 94.2 | 230 | 47 | BB | 19.0 | 2650 | -40...+85 | 119 | 119 | 38 | 4656N | LZ120/1.5 | LZ30K | - |
| 4656N-KR1 | 160 | 94.2 | 230 | 47 | BB | 19.0 | 2650 | -40...+85 | 119 | 119 | 38 | 4656N | LZ120/1.5 | - | PMFA120T |
| 4600N-KR0 | 180 | 105.9 | 115 | 50 | SB | 18.0 | 3100 | -10...+60 | 119 | 119 | 38 | 4600N | LZ120/1.5 | LZ30K | - |
| 4600N-KR1 | 180 | 105.9 | 115 | 50 | SB | 18.0 | 3100 | -10...+60 | 119 | 119 | 38 | 4600N | LZ120/1.5 | - | PMFA120T |
| 4606N-KR0 | 160 | 94.2 | 115 | 46 | SB | 19.0 | 2650 | -10...+55 | 119 | 119 | 38 | 4606N | LZ120/1.5 | LZ30K | - |
| 4606N-KR1 | 160 | 94.2 | 115 | 46 | SB | 19.0 | 2650 | -10...+55 | 119 | 119 | 38 | 4606N | LZ120/1.5 | - | PMFA120T |
| ACI4420HH-KR0 | 180 | 105.9 | 230 | 42 | BB | 4.4 | 3350 | -20...+75 | 119 | 119 | 38 | ACI4420HH | LZ120/1.5 | LZ30K | - |
| ACI4420HH-KR1 | 180 | 105.9 | 230 | 42 | BB | 4.4 | 3350 | -20...+75 | 119 | 119 | 38 | ACI4420HH | LZ120/1.5 | - | PMFA120T |
| W2E142-BB01-01-KR0 | 330 | 194 | 230 | 52 | BB | 29.0 | 2800 | -25...+55 | 150 | 172 | 38 | W2E142-BB01-01 | LZ120/1.5 | 03749-2-4039 | - |
| W2E142-BB01-01-KR1 | 330 | 194 | 230 | 52 | BB | 29.0 | 2800 | -25...+55 | 150 | 172 | 38 | W2E142-BB01-01 | LZ120/1.5 | - | PMFA160 |

ebm-papst UK Ltd, Chelmsford Business Park, Chelmsford, Essex, CM2 5EZ
01245 468555 sales@uk.ebmpapst.com www.ebmpapst.co.uk