60x10mm Replacement Ball Bearing Computer Case Fan w/ TX3 Connector

Product ID: FAN6X1TX3



This versatile 60mm fan is an ideal replacement fan for keeping your computer running cool. The fan can be powered through a TX3 connection, and features a dual ball bearing design that ensures reliable cooling and longer fan lifespan.

The fan can be used to replace the fan component of some CPU coolers or mounted to the side panel of a computer case and features a tachometer pin on the TX3 motherboard connector that provides the host system with fan operating status information.

Certifications, Reports and Compatibility

Applications

• Replace a noisy or failed computer case fan

• Install into a computer to increase air flow and cooling

Features

• Dual ball bearing design

• 3-pin connector with tachometer wire

• Includes a 3-pin to 4-pin LP4 Adapter

Hardware		
	Warranty	2 Years
	Number of Conductors	3
	Fan Bearing Type	Ball Bearing
Performance		
	Air Flow Rate	15.49 CFM
	Noise Level	28 dBA
	MTBF	56,609 Hours
	Fan RPM	4000
Connector(s)		
	Connector Type(s)	1 - Fan (3 pin, TX3)
Power		
	Input Voltage	12V DC
	Input Current	160mA
	Output Voltage	12V DC
	Power Consumption (In Watts)	1.92W
Environmental		
	Operating Temperature	-10 to 80
Physical Characteristics		
	Color	Black
	Material	Plastic
	Product Length	2.4 in [60 mm]
	Product Width	0.4 in [1 cm]
	Product Height	2.4 in [6 cm]
	Weight of Product	1.0 oz [28 g]

Packaging Information		
	Package Quantity	1
	Package Length	3.3 in [8.4 cm]
	Package Width	2.7 in [6.8 cm]
	Package Height	1.2 in [3.0 cm]
	Shipping (Package) Weight	1.7 oz [48 g]
What's in the Box		
	Included in Package	1 - 6cm Case Fan
		1 - 3-pin to 4-pin LP4 Adapter Cable

Product appearance and specifications are subject to change without notice.