

2-Port DVI USB KVM Switch Kit with Audio

TK-204UK (v2.1R)

The 2-Port DVI USB KVM Switch Kit with Audio manages two computers with one set of console controls. Control two computers with DVI and USB ports at the touch of a button with one set of microphone / speakers, USB keyboard, USB mouse, and DVI monitor.

Simply plug everything in to start sharing your HD DVI monitor with two Mac or Windows computers. No need for additional cabling, all required cables are included. Network printers, storage drives, flash drives and more by connecting to the two bonus USB ports on the front of the switch. Listen to music on one computer while working on the other. Switch between computer by pressing the convenient switch button or by programming shortcut Hotkey commands.

PRODUCT OVERVIEW

- Manage two PCs or Macs with one set of console controls
- Share an HD DVI monitor with two computers
- Two bonus USB ports to network printers, storage devices, and more
- Listen to music on one computer while working on the other
- All required cables are included

FEATURES

- 2 x USB keyboard and mouse ports
- 2 x bonus USB 2.0 ports
- 2-way audio support for uninterrupted multimedia experience across multi-platforms
- Independent simultaneous switching of both PC and audio channels
- Advanced keyboard and mouse support
- Multi-platform support for Windows, Mac, and Linux
- Hot-plug PCs without powering down the KVM switch (Window OS)
- Digital video resolution up to 1920 x 1200 and analog video resolution up to 2048 x 1536
- Integrated High-Bandwidth Digital Content Protection (HDCP) and Transition Minimized Differential Signaling (TDMS)
- No CD installation required—simply plug and go
- 2-year limited warranty

2-Port DVI USB KVM Switch Kit with Audio

TK-204UK (v2.1R)

SPECIFICATIONS

HARDWARE	
Connections	• 2 computers
Standard	• DVI-I and DVI-D Compliant • USB 2.0 compliant
PC Port Connector	• 2 x USB type B • 2 x DVI-I (integrated speaker / microphone support)
Console Port Connector	• 2 x USB type A (keyboard and mouse) • 2 x USB type A (USB 2.0 devices) • 1x DVI-I single link • 1 x 3.5 mm speaker jack • 1 x 3.5 mm microphone jack
Cable	• 2 x detachable DVI / speaker and microphone combo cable • 2 x USB type A to type B cable
PC Selection	• Push button, keyboard Hotkey commands (Windows only)
LED	• Green: Computer 1 • Blue: Computer 2
VGA Resolution	• 1920 x 1200 (digital) • 2048 x 1536 (analog)
Power	• Input: 100~240 VAC, 50~60Hz • Output: 5V DC, 2A external power adapter
Dimensions	• 165 × 75 × 33 mm (6.5 x 3.0 x 1.3 in.)
Weight	• 160 g (5.6 oz)
Temperature	• Operating: 0°C ~ 40°C (32° ~104°F) • Storage: -20°C ~ 60°C (-4° ~ 140°F)
Humidity	• Max 90% (Non-condensing)
Certifications	• CE, FCC

2-Port DVI USB KVM Switch Kit with Audio

TK-204UK (v2.1R)

NETWORKING SOLUTIONS



PACKAGE CONTENTS

TK-204UK
Quick Installation Guide
2 x DVI / Audio combo KVM cable (1.2 m / 4 ft.)
2 x USB type A to type B cable (1.2 m / 4 ft.)
Power Adapter (5V DC, 2A)

RELATED PRODUCTS

TK-214i	2-Port DVI USB KVM Switch Kit with Audio
TK-217i	2-Port USB KVM Switch
TK-209K	2-Port USB KVM Switch Kit w/ Audio

CONTACT INFORMATION

TRENDnet

20675 Manhattan Place,Torrance, CA 90501 USA
Tel: 1-310-961-5500
Fax: 1-310-961-5511
Web: www.trendnet.com
Email: sales@trendnet.com
1-888-326-6061

TRENDnet is a registered trademark. Other Brands and product names are trademarks of their respective holders. Information provided in this document pertain to TRENDnet products and is subject to change at any time, without notice. For the most recent product information please visit http://www.trendnet.com Copyright ©TRENDnet.All Rights Reserved.