BOT LIGHTING
FOR A BRIGHT FUTURE


# A60 LED SURGE PROTECTION

SLD1011X2SP

11,0 W - 1055lm - 2700K

A+ | 15.000 H | NOT DIMMABLE | 15.000 | INSTANT






| DIMENSIONS | A | B | C |
|---|---|---|---|
| 1 | 109 | --- | 60 |

| GENERAL INFORMATIONS | |
|---|---|
| Code | SLD1011X2SP |
| Ean | 8031453021221 |
| Family | A60 LED SURGE PROTECTION |
| Technology | LED |
| Energy class | A+ |
| Operating temperature (° C) | -20 - +40 |

| PACKAGING | |
|---|---|
| Packaging | BOX |
| Pack | 10 / 50 |

| LIGHTING DATA | |
|---|---|
| Kelvin (°) | 2700 |
| Lumen | 1055 |
| Beam (°) | 200 |
| Luminous ef(cacy (lm / W) | 95,91 |
| Color rendering (CRI) | >80 |

| TECHNICAL FEATURES | |
|---|---|
| Base | E27 |
| Power (W) | 11,0 |
| Equivalence (W) | 75 |
| Supply voltage (V) / Max (V) | 220 / 240 |
| Power frequency (Hz) | 50/60 |
| Power factor | >0,5 |
| Dimmer compatibility | NO |

SHOT BOT LIGHTING | Kkai | AIRAM BOT LIGHTING

**Bot Lighting srl**
Via Lombardia, 37/39 – 30030 Cazzago di Pianiga (VE) Italy - T. +39.041.51.29.411 – F. +39.041.51.01.715
www.botlighting.it – ordini@botlighting.it – info@botlighting.it

BOT LIGHTING
FOR A BRIGHT FUTURE

# A60 LED SURGE PROTECTION

SLD1011X2SP

11,0W - 1055lm - 2700K

- Power surge protection system up to 2.5KV

**Bot Lighting srl**
Via Lombardia, 37/39 – 30030 Cazzago di Pianiga (VE) Italy - T. +39.041.51.29.411 – F. +39.041.51.01.715
www.botlighting.it – ordini@botlighting.it – info@botlighting.it